



PR411DR-SET consist of PR411DR-BRD access controller module and TRP 40/16/18 power transformer factory preinstalled in ME-1 metal enclosure with space for 7 Ah/12 V back-up battery and tamper contact.

Features:

- power supply 230 VAC (+/-15%), 50 Hz
 - tamper
 - place for 7 Ah/12 V battery
 - closing with four screws on the door side
 - environmental conditions of operation:
 - temperature from +5°C to +40°C
 - humidity from 10% to 95%
 - dimensions: 285.0 x 295.0 x 88.0 mm (height x width x thickness)
 - weight: ≈3500.0 g
 - CE mark
- **benefits:**
 - complete solution. The kit contains all (apart from readers) devices needed to build fully functional access control point
 - possibility of ceiling mounting
 - direct view to access controller state thanks to window in the enclosure
 - esthetical metal enclosure
 - quick and easy installation thanks to enclosed accessories
 - **set includes:**
 - PR411DR-BRD module access controller
 - mains transformer TRP 40/16/18
 - proximity card of Master user
 - set of jumpers for addressing the controller
 - metal enclosure with tamper switch, DIN rail
 - mounting screws
 - back-up battery and transformer cables
 - manuals

Ordering guide

<i>Item</i>	<i>Description</i>
PR411DR-SET	Set includes: PR411DR-BRD access controller; ME-1 metal enclosure with TRP 40/16/18 transformer

Legal Notice

This document is not intended to be a technical specification of the product and has informative character only. The Manufactures of product reserves right to change its characteristic without notice. The product features listed in this document refer to the entire series and depends on particular product version, configuration and additional equipment.

RevC © 2021 ROGER sp. z o.o. sp. k. All rights reserved.

This document is a subject to the Terms of Use in their current version published at the www.roger.pl